



\*\*\*Spare part\*\*\* SIMATIC S7-200, Analog input EM 231, only for S7-22X CPU, 4 AI, 0-10V DC, 12 bit converter

Input current	
from load voltage L+ (without load), max.	60 mA
from backplane bus 5 V DC, max.	20 mA
Power loss	
Power loss, typ.	2 W
Analog inputs	
Number of analog inputs	4; Difference
permissible input voltage for voltage input (destruction limit), max.	30 V
permissible input current for current input (destruction limit), max.	32 mA
Input ranges	
<ul style="list-style-type: none"> <li>• Voltage</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Current</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• Thermocouple</li> </ul>	No
<ul style="list-style-type: none"> <li>• Resistance thermometer</li> </ul>	No
<ul style="list-style-type: none"> <li>• Resistance</li> </ul>	No
Input ranges (rated values), voltages	
<ul style="list-style-type: none"> <li>• 0 to +5 V                             <ul style="list-style-type: none"> <li>— Input resistance (0 to 5 V)</li> </ul> </li> </ul>	Yes 10 MΩ
<ul style="list-style-type: none"> <li>• 0 to +10 V                             <ul style="list-style-type: none"> <li>— Input resistance (0 to 10 V)</li> </ul> </li> </ul>	Yes 10 MΩ
<ul style="list-style-type: none"> <li>• -2.5 V to +2.5 V                             <ul style="list-style-type: none"> <li>— Input resistance (-2.5 V to +2.5 V)</li> </ul> </li> </ul>	Yes 10 MΩ
<ul style="list-style-type: none"> <li>• -5 V to +5 V                             <ul style="list-style-type: none"> <li>— Input resistance (-5 V to +5 V)</li> </ul> </li> </ul>	Yes 10 MΩ
Input ranges (rated values), currents	
<ul style="list-style-type: none"> <li>• 0 to 20 mA                             <ul style="list-style-type: none"> <li>— Input resistance (0 to 20 mA)</li> </ul> </li> </ul>	Yes 10 MΩ
Thermocouple (TC)	
Temperature compensation <ul style="list-style-type: none"> <li>— parameterizable</li> </ul>	No
Cable length	
<ul style="list-style-type: none"> <li>• shielded, max.</li> </ul>	100 m; to the sensor
Analog value generation for the inputs	
Integration and conversion time/resolution per channel	
<ul style="list-style-type: none"> <li>• Resolution with overrange (bit including sign), max.</li> </ul>	12 bit
<ul style="list-style-type: none"> <li>• Interference voltage suppression for interference frequency <math>f_1</math> in Hz</li> </ul>	40 dB, DC to 60 V for interference frequency 50 / 60 Hz
<ul style="list-style-type: none"> <li>• Conversion time (per channel)</li> </ul>	250 μs
Displayable conversion value range	

- bipolar signals
- unipolar signals

-32 000 to +32 000

[0 to 32 000](#)

#### Errors/accuracies

Interference voltage suppression for  $f = n \times (f_1 \pm 1 \%)$ ,  $f_1 =$  interference frequency

- Common mode voltage, max.

12 V

#### Interrupts/diagnostics/status information

Diagnostics indication LED

- external fault EXTf (red)

Yes

#### Potential separation

Potential separation analog inputs

- Potential separation analog inputs

No

#### connection method

Plug-in I/O terminals

No

#### Dimensions

Width

71.2 mm

Height

80 mm

Depth

62 mm

#### Weights

Weight, approx.

183 g

last modified:

8/23/2023 