SIEMENS

Data sheet

6ES7521-1BL00-0AB0



SIMATIC S7-1500, digital input module DI 32x24 V DC HF, 32 channels in groups of 16; of which 2 inputs as counters can be used; input delay 0.05..20 ms input type 3 (IEC 61131); diagnostics; hardware interrupts: front connector (screw terminals or push-in) to be ordered separately

Figure similar

Figure similar		
General information		
Product type designation	DI 32x24VDC HF	
HW functional status	from FS04	
Firmware version	V2.2.1	
FW update possible	Yes	
Product function		
• I&M data	Yes; I&M0 to I&M3	
 Isochronous mode 	Yes	
Prioritized startup	Yes	
Engineering with		
 STEP 7 TIA Portal configurable/integrated from version 	V13 SP1 / -	
 STEP 7 configurable/integrated from version 	V5.5 SP3 / -	
 PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1	
 PROFINET from GSD version/GSD revision 	V2.3 / -	
Operating mode		
• DI	Yes	
Counter	Yes	
 Oversampling 	No	
• MSI	Yes	
Supply voltage		
Rated value (DC)	24 V	
permissible range, lower limit (DC)	19.2 V	
permissible range, upper limit (DC)	28.8 V	
Reverse polarity protection	Yes	
Input current		
Current consumption, max.	40 mA; 20 mA per group with 24 V DC supply	
Power		
Power available from the backplane bus	1.1 W	
Power loss		
Power loss, typ.	4.2 W	
Digital inputs		
Number of digital inputs	32	
Digital inputs, parameterizable	Yes	
Source/sink input	P-reading	
Input characteristic curve in accordance with IEC 61131, type 3	Yes	
Digital input functions, parameterizable		
Gate start/stop	Yes	
 Freely usable digital input 	Yes	
Counter		

— Number, max.	2
— Counting frequency, max.	6 kHz; FS04 and FW V2.2.1 or higher
— Counting width	32 bit
— Counting direction up/down	Up
Input voltage	24 V
Rated value (DC)for signal "0"	-30 to +5 V
• for signal "1"	+11 to +30V
Input current	+11 to +30V
• for signal "1", typ.	2.5 mA
Input delay (for rated value of input voltage)	2.5 IIIA
for standard inputs	
— parameterizable	Yes; 0.05 / 0.1 / 0.4 / 1.6 / 3.2 / 12.8 / 20 ms
— at "0" to "1", min.	0.05 ms
— at "0" to "1", max.	20 ms
— at "1" to "0", min.	0.05 ms
— at "1" to "0", max.	20 ms
for interrupt inputs	20
— parameterizable	Yes
for technological functions	
— parameterizable	Yes
Cable length	
shielded, max.	1 000 m
• unshielded, max.	600 m
Encoder	
Connectable encoders	
• 2-wire sensor	Yes
 permissible quiescent current (2-wire sensor), max. 	1.5 mA
Isochronous mode	
Filtering and processing time (TCI), min.	80 μs; At 50 μs filter time
Bus cycle time (TDP), min.	250 μs
Interrupts/diagnostics/status information	
	Yes
Interrupts/diagnostics/status information	
Interrupts/diagnostics/status information Diagnostics function	
Interrupts/diagnostics/status information Diagnostics function Alarms	Yes
Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm	Yes
Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm • Hardware interrupt	Yes
Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm • Hardware interrupt Diagnoses	Yes Yes Yes
Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm • Hardware interrupt Diagnoses • Monitoring the supply voltage	Yes Yes Yes Yes
Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm • Hardware interrupt Diagnoses • Monitoring the supply voltage • Wire-break	Yes Yes Yes Yes Yes Yes; to I < 350 µA
Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm • Hardware interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit	Yes Yes Yes Yes Yes Yes; to I < 350 µA
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED	Yes Yes Yes Yes Yes Yes; to I < 350 µA No
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED	Yes Yes Yes Yes Yes Yes; to I < 350 µA No Yes; green LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED	Yes Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED)	Yes Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics	Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics	Yes Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics	Yes Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation Potential separation channels between the channels	Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of	Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED REROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of between the channels and backplane bus	Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED Yes; red LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of	Yes Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of between the channels and backplane bus between the channels and the power supply of the	Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED Yes; red LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of between the channels and backplane bus between the channels and the power supply of the electronics	Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED Yes; red LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED RUN LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics for module diagnostics between the channels between the channels and backplane bus between the channels and backplane bus between the channels and the power supply of the electronics Isolation	Yes Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED Yes; red LED No
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED REROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus between the channels and the power supply of the electronics Isolation Isolation tested with	Yes Yes Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED Yes; red LED No
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of between the channels and backplane bus between the channels and the power supply of the electronics Isolation Isolation tested with Standards, approvals, certificates	Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED Yes; red LED Your red LED Yes red LED Yes red LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RROR LED RIN LED FRROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus between the channels and the power supply of the electronics Isolation Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions	Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED Yes; red LED Your red LED Yes red LED Yes red LED
Interrupts/diagnostics/status information Diagnostics function Alarms Diagnostic alarm Hardware interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED RUN LED RON LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus between the channels and the power supply of the electronics Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions Ambient conditions	Yes Yes Yes; to I < 350 µA No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; red LED Yes; red LED Yes; red LED Yes; red LED Your red LED Yes red LED Yes red LED

 horizontal installation, max. 	60 °C
 vertical installation, min. 	-30 °C; From FS05
• vertical installation, max.	40 °C
Altitude during operation relating to sea level	
 Installation altitude above sea level, max. 	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	35 mm
Height	147 mm
Depth	129 mm
Weights	
Weight, approx.	260 g

last modified: 8/16/2023 🖸