

185182300040

PIR movement and presence detector 10 A




Technical description: Movement and presence detector, Movement and presence detector, Single pole switching, 10 A, Programming: Standard, Contact circuit: voltage output, Special version: Push-button connection, AC supply version, nominal voltage 230 V, operating from 96 to 253 V, rated power 1.5 VA, ambient temperature from -10 to +50 °C

Commercial description: Movement and presence detector with Push-in terminals suitable for indoor installation. The Type 18.51 boasts a large detection area (up to 64m²) and is designed to detect both presence, in areas with low activity from occupants, and movement through transit areas or increased activity. The installation, which can be either wall-mounted or recessed, is particularly fast thanks to the cable connection with push-in terminals.

[BROWSE PRODUCT PAGE](#)

Technical Features:

App manageable:	NO
Contact configuration:	1 NO
Dimensions:	84x35.1x84 mm
Protection category:	IP 40
Rated current contact:	10 A
Rated voltage contact:	230 V AC
Supply version:	AC supply version
Type of installation:	Movement and presence detector
Certifications and quality approvals (according to code):	

Need more information?

[Contact our sales](#) [Find a dealer](#)