

18518230B300

PIR movement and presence detector 10 A




Technical description: Movement and presence detector, Movement and presence detector, Single pole switching, 10 A, Programming: Bluetooth, Contact circuit: Volt-free output contact, AC supply version, nominal voltage 230 V, operating from 96 to 253 V, rated power 1.5 VA, ambient temperature from -10 to +50 °C

Commercial description: Movement and presence detector with Push-in terminals suitable for indoor installation. The Type 18.51 boasts a large detection area (up to 64m²) and is designed to detect both presence, in areas with low activity from occupants, and movement through transit areas or increased activity. The installation, which can be either wall-mounted or recessed, is particularly fast thanks to the cable connection with push-in terminals.

[BROWSE PRODUCT PAGE](#)

Technical Features:

Contact configuration:	1 NO
Dimensions:	84x35.1x84 mm
Manageable with app:	YES
Protection category:	IP 40
Rated contact voltage:	230 V AC
Rated current (contacts):	10 A
Supply:	AC supply version
Type of installation:	Movement and presence detector
Certifications and quality approvals (according to type):	

Need more information?

[Contact our sales](#) [Find a dealer](#)